



Scan to see a full specifications, installation and agency certification information.

APPLICATIONS:

APPLIANCE | ELECTRICAL | HVAC/R | MARINE | POOL & SPA | RV



FEATURES

- ✓ Reduces in-rush current/draw necessary at startup by up to 70%
- ✓ Prolong the life of A/C by reducing excessive torque, wear and tear
- ✓ Reduce loud noises, light flickering, and breaker trips
- ✓ Built-in self-learning algorithm
- ✓ Over-current protection
- ✓ Over/under voltage monitoring
- ✓ Built-in start capacitor
- ✓ LED fault indicators
- ✓ Ultrasonic sealed tamper-proof enclosure
- ✓ Installation hardware is included

SPECIFICATIONS

- **Inputs:** L1 & L2
- **Nominal voltage:** 120 VAC, 240 VAC
- **Over voltage limits:** 120 VAC nominal = 140 VAC, 240 VAC nominal = 250 VAC
- **Under voltage limits:** 120 VAC nominal = 95 VAC, 240 VAC nominal = 195 VAC
- **Outputs:** Compressor
- **Current:** Maximum nominal = 32A
- **Over current limits:**
 - ICM870-32A = 40A
- **Operating temperature:** -40°F to 131°F (-40°C to 55°C)
- **Storage temperature:** -40°F to 149°F (-40°C to 65°C)
- **Humidity:** 0-95% non-condensing
- **Enclosure:** IP65

OVERVIEW

The **ICM870** Soft Start is intended for residential, commercial, RV & marine applications. The **ICM870** integrates compressor or motor in-rush current over startup time, thus reducing peak current demand on a power supply source by up to 70%.

The **ICM870** will monitor system health including voltage, current, compressor startup and integrity. Utilizing a built-in self learning algorithm the **ICM870** soft start delivers peak in-rush current per application.

ICM870 COMPARABLE AMPERAGE CROSSES

The **ICM870-32A** models cross to the comparable amperage models from the following manufacturer's

- Dometic** (Smart Start)
- Hyper Engineering** (Sure Start)
- Micro-Air** (Easy Start)
- Network RV** (Soft Start)

Content and specifications on sell sheets subject to change without notice.